

Fortinet

Exam Questions NSE7_EFW-6.4

Fortinet NSE 7 - Enterprise Firewall 6.4



NEW QUESTION 1

View the exhibit, which contains a partial routing table, and then answer the question below.

Assuming all the appropriate firewall policies are configured, which of the following pings will FortiGate route? (Choose two.)

- A. Source IP address 10.1.0.24, Destination IP address 10.72.3.20.
- B. Source IP address 10.72.3.27, Destination IP address 10.1.0.52.
- C. Source IP address 10.72.3.52, Destination IP address 10.1.0.254.
- D. Source IP address 10.73.9.10, Destination IP address 10.72.3.15.

Answer: BC

NEW QUESTION 2

Which statements about bulk configuration changes using FortiManager CLI scripts are correct? (Choose two.)

- A. When executed on the Policy Package, ADOM database, changes are applied directly to the managed FortiGate.
- B. When executed on the Device Database, you must use the installation wizard to apply the changes to the managed FortiGate.
- C. When executed on the All FortiGate in ADOM, changes are automatically installed without creating a new revision history.
- D. When executed on the Remote FortiGate directly, administrators do not have the option to review the changes prior to installation.

Answer: BD

Explanation:

CLI scripts can be run in three different ways: Device Database: By default, a script is executed on the device database. It is recommend you run the changes on the device database (default setting), as this allows you to check what configuration changes you will send to the managed device. Once scripts are run on the device database, you can install these changes to a managed device using the installation wizard.

Policy Package, ADOM database: If a script contains changes related to ADOM level objects and policies, you can change the default selection to run on Policy Package, ADOM database and can then be installed using the installation wizard.

Remote FortiGate directly (through CLI): A script can be executed directly on the device and you don't need to install these changes using the installation wizard. As the changes are directly installed on the managed device, no option is provided to verify and check the configuration changes through FortiManager prior to executing it.

NEW QUESTION 3

View the exhibit, which contains the output of a real-time debug, and then answer the question below.

Which of the following statements is true regarding this output? (Choose two.)

- A. This web request was inspected using the root web filter profile.
- B. FortiGate found the requested URL in its local cache.
- C. The requested URL belongs to category ID 52.
- D. The web request was allowed by FortiGate.

Answer: BC

NEW QUESTION 4

View the IPS exit log, and then answer the question below.

```
# diagnose test application ipsmonitor 3 ipsengine exit log"
```

```
pid = 93 (cfg), duration = 5605322 (s) at Wed Apr 19 09:57:26 2017 code = 11, reason: manual
```

What is the status of IPS on this FortiGate?

- A. IPS engine memory consumption has exceeded the model-specific predefined value.
- B. IPS daemon experienced a crash.
- C. There are communication problems between the IPS engine and the management database.
- D. All IPS-related features have been disabled in FortiGate's configuration.

Answer: D

Explanation:

The command `diagnose test application ipsmonitor` includes many options that are useful for troubleshooting purposes. Option 3 displays the log entries generated every time an IPS engine process stopped. There are various reasons why these logs are generated: Manual: Because of the configuration, IPS no longer needs to run (that is, all IPS-related features have been disabled)

NEW QUESTION 5

When does a RADIUS server send an Access-Challenge packet?

- A. The server does not have the user credentials yet.
- B. The server requires more information from the user, such as the token code for two-factor authentication.
- C. The user credentials are wrong.
- D. The user account is not found in the server.

Answer: B

NEW QUESTION 6

A FortiGate is configured as an explicit web proxy. Clients using this web proxy are reposting DNS errors when accessing any website. The administrator executes the following debug commands and observes that the `n-dns-timeout` counter is increasing:

What should the administrator check to fix the problem?

- A. The connectivity between the FortiGate unit and the DNS server.
- B. The connectivity between the client workstations and the DNS server.
- C. That DNS traffic from client workstations is allowed by the explicit web proxy policies.
- D. That DNS service is enabled in the explicit web proxy interface.

Answer: A

NEW QUESTION 7

Refer to the exhibit, which contains the debug output of `diagnose dvm device list`.

Which two statements about the output shown in the exhibit are correct? (Choose two.)

- A. ADOMs are disabled on the FortiManager
- B. The FortiGate configuration is in sync with latest running revision history.
- C. There are pending device-level changes yet to be installed on Local-FortiGate.
- D. The policy package has been modified for Local-FortiGate.

Answer: BC

NEW QUESTION 8

What global configuration setting changes the behavior for content-inspected traffic while FortiGate is in system conserve mode?

- A. `av-failopen`
- B. `mem-failopen`
- C. `utm-failopen`
- D. `ips-failopen`

Answer: A

Explanation:

https://help.fortinet.com/fos50hlp/54/Content/FortiOS/fortigate-security-profiles-54/Other_Profile_Consideratio

NEW QUESTION 9

Which two statements about an auxiliary session are true? (Choose two.)

- A. With the auxiliary session setting enabled, ECMP traffic is accelerated to the NP6 processor.
- B. With the auxiliary session setting enabled, two sessions will be created in case of routing change.
- C. With the auxiliary session setting disabled, for each traffic path, FortiGate will use the same auxiliary session.
- D. With the auxiliary session disabled, only auxiliary sessions will be offloaded.

Answer: CD

NEW QUESTION 10

An administrator has decreased all the TCP session timers to optimize the FortiGate memory usage. However, after the changes, one network application started to have problems. During the troubleshooting, the administrator noticed that the FortiGate deletes the sessions after the clients send the SYN packets, and before the arrival of the SYN/ACKs. When the SYN/ACK packets arrive to the FortiGate, the unit has already deleted the respective sessions. Which TCP session timer must be increased to fix this problem?

- A. TCP half open.
- B. TCP half close.
- C. TCP time wait.
- D. TCP session time to live.

Answer: A

Explanation:

http://docs-legacy.fortinet.com/fos40hlp/43prev/wwhelp/wwhimpl/common/html/wwhelp.htm?context=fgt&file=CLI_get_Commands.58.25.html

The tcp-halfopen-timer controls for how long, after a SYN packet, a session without SYN/ACK remains in the table.

The tcp-halfclose-timer controls for how long, after a FIN packet, a session without FIN/ACK remains in the table.

The tcp-timewait-timer controls for how long, after a FIN/ACK packet, a session remains in the table. A closed session remains in the session table for a few seconds more to allow any out-of-sequence packet.

NEW QUESTION 10

Refer to the exhibit, which contains a TCL script configuration on FortiManager.

An administrator has configured the TCL script on FortiManager, but failed to apply any changes to the managed device after being executed. Why did the TCL script fail to make any changes to the managed device?

- A. Changes in an interface configuration can only be done by CLI script.
- B. The TCL script must start with #include <>.
- C. Incomplete commands are ignored in TCL scripts.
- D. The TCL command run_cmd has not been created.

Answer: D

NEW QUESTION 13

View the exhibit, which contains the output of get sys ha status, and then answer the question below.

Which statements are correct regarding the output? (Choose two.)

- A. The slave configuration is not synchronized with the master.
- B. The HA management IP is 169.254.0.2.
- C. Master is selected because it is the only device in the cluster.
- D. port 7 is used the HA heartbeat on all devices in the cluster.

Answer: AD

NEW QUESTION 17

View the exhibit, which contains the partial output of an IKE real-time debug, and then answer the question below.

Why didn't the tunnel come up?

- A. The pre-shared keys do not match.
- B. The remote gateway's phase 2 configuration does not match the local gateway's phase 2 configuration.
- C. The remote gateway's phase 1 configuration does not match the local gateway's phase 1 configuration.
- D. The remote gateway is using aggressive mode and the local gateway is configured to use man mode.

Answer: C

NEW QUESTION 22

An administrator added the following Ipsec VPN to a FortiGate configuration:

```
configvpn ipsec phasel -interface edit "RemoteSite"  
set type dynamic  
set interface "port1" set mode main  
set psksecret ENC LCVkCiK2E2PhVUzZe next  
end  
config vpn ipsec phase2-interface edit "RemoteSite"  
set phasel name "RemoteSite" set proposal 3des-sha256  
next end
```

However, the phase 1 negotiation is failing. The administrator executed the IKF real time debug while attempting the Ipsec connection. The output is shown in the

exhibit.

What is causing the IPsec problem in the phase 1 ?

- A. The incoming IPsec connection is matching the wrong VPN configuration
- B. The phrase-1 mode must be changed to aggressive
- C. The pre-shared key is wrong
- D. NAT-T settings do not match

Answer: C

NEW QUESTION 26

View these partial outputs from two routing debug commands:

Which outbound interface will FortiGate use to route web traffic from internal users to the Internet?

- A. Both port1 and port2
- B. port3
- C. port1
- D. port2

Answer: C

NEW QUESTION 29

Which of the following conditions must be met for a static route to be active in the routing table? (Choose three.)

- A. The next-hop IP address is up.
- B. There is no other route, to the same destination, with a higher distance.
- C. The link health monitor (if configured) is up.
- D. The next-hop IP address belongs to one of the outgoing interface subnets.
- E. The outgoing interface is up.

Answer: CDE

Explanation:

A configured static route only goes to routing table from routing database when all the following are met :

- The outgoing interface is up
- There is no other matching route with a lower distance
- The link health monitor (if configured) is successful
- The next-hop IP address belongs to one of the outgoing interface subnets

NEW QUESTION 30

What configuration changes can reduce the memory utilization in a FortiGate? (Choose two.)

- A. Reduce the session time to live.
- B. Increase the TCP session timers.
- C. Increase the FortiGuard cache time to live.
- D. Reduce the maximum file size to inspect.

Answer: AD

NEW QUESTION 33

Four FortiGate devices configured for OSPF connected to the same broadcast domain. The first unit is elected as the designated router The second unit is elected as the backup designated router Under normal operation, how many OSPF full adjacencies are formed to each of the other two units?

- A. 1
- B. 2
- C. 3
- D. 4

Answer: B

NEW QUESTION 36

Which two tasks are automated using the Install Wizard on FortiManager? (Choose two.)

- A. Preview pending configuration changes for managed devices.
- B. Add devices to FortiManager.
- C. Import policy packages from managed devices.
- D. Install configuration changes to managed devices.
- E. Import interface mappings from managed devices.

Answer: AD

Explanation:

https://help.fortinet.com/fmgr/50hlp/56/5-6-2/FortiManager_Admin_Guide/1000_Device%20Manager/1200_ins

There are 4 main wizards: Add Device: is used to add devices to central management and import their configurations.

Install: is used to install configuration changes from Device Manager or Policies & Objects to the managed devices. It allows you to preview the changes and, if the administrator doesn't agree with the changes, cancel and modify them.

Import policy: is used to import interface mapping, policy database, and objects associated with the managed devices into a policy package under the Policy & Object tab. It runs with the Add Device wizard by default and may be run at any time from the managed device list.

Re-install policy: is used to perform a quick install of the policy package. It doesn't give the ability to preview the changes that will be installed to the managed device.

NEW QUESTION 40

View the global IPS configuration, and then answer the question below.

Which of the following statements is true regarding this configuration?

- A. IPS will scan every byte in every session.
- B. FortiGate will spawn IPS engine instances based on the system load.
- C. New packets will be passed through without inspection if the IPS socket buffer runs out of memory.
- D. IPS will use the faster matching algorithm which is only available for units with more than 4 GB memory.

Answer: A

NEW QUESTION 45

What does the dirty flag mean in a FortiGate session?

- A. Traffic has been blocked by the antivirus inspection.
- B. The next packet must be re-evaluated against the firewall policies.
- C. The session must be removed from the former primary unit after an HA failover.
- D. Traffic has been identified as from an application that is not allowed.

Answer: B

Explanation:

<https://kb.fortinet.com/kb/viewContent.do?externalId=FD40119&sliceId=1>

NEW QUESTION 49

Examine the output of the 'get router info ospf interface' command shown in the exhibit; then answer the question below.

Which statements are true regarding the above output? (Choose two.)

- A. The port4 interface is connected to the OSPF backbone area.
- B. The local FortiGate has been elected as the OSPF backup designated router.
- C. There are at least 5 OSPF routers connected to the port4 network.
- D. Two OSPF routers are down in the port4 network.

Answer: AC

Explanation:

on BROADCAST network there are 4 neighbors, among which 1*DR +1*BDR. So our FG has 4 neighbors, but create adjacency only with 2 (with DR and BDR). 2 neighbors DRother (not down).

NEW QUESTION 50

Examine the partial output from two web filter debug commands; then answer the question below:

Based on the above outputs, which is the FortiGuard web filter category for the web site www.fgt99.com?

- A. Finance and banking
- B. General organization.
- C. Business.
- D. Information technology.

Answer: C

NEW QUESTION 51

Which statement is true regarding File description (FD) conserve mode?

- A. IPS inspection is affected when FortiGate enters FD conserve mode.
- B. A FortiGate enters FD conserve mode when the amount of available description is less than 5%.
- C. FD conserve mode affects all daemons running on the device.
- D. Restarting the WAD process is required to leave FD conserve mode.

Answer: B

NEW QUESTION 53

A FortiGate device has the following LDAP configuration:

The LDAP user student cannot authenticate. The exhibit shows the output of the authentication real time debug while testing the student account:

Based on the above output, what FortiGate LDAP settings must the administrator check? (Choose two.)

- A. cnid.
- B. username.
- C. password.
- D. dn.

Answer: BC

Explanation:

<https://kb.fortinet.com/kb/viewContent.do?externalId=13141>

NEW QUESTION 57

The logs in a FSSO collector agent (CA) are showing the following error: failed to connect to registry: PIKA1026 (192.168.12.232)
What can be the reason for this error?

- A. The CA cannot resolve the name of the workstation.
- B. The FortiGate cannot resolve the name of the workstation.
- C. The remote registry service is not running in the workstation 192.168.12.232.
- D. The CA cannot reach the FortiGate with the IP address 192.168.12.232.

Answer: C

Explanation:

<https://kb.fortinet.com/kb/documentLink.do?externalID=FD30548>

NEW QUESTION 61

Examine the output of the 'get router info ospf neighbor' command shown in the exhibit; then answer the question below.

Which statements are true regarding the output in the exhibit? (Choose two.)

- A. The interface ToRemote is OSPF network type point-to-point.
- B. The OSPF router with the ID 0.0.0.2 is the designated router for the ToRemote network.
- C. The local FortiGate is the backup designated router for the wan1 network.
- D. The OSPF routers with the IDs 0.0.0.69 and 0.0.0.117 are both designated routers for the wan1 network.

Answer: AC

Explanation:

<https://www.cisco.com/c/en/us/support/docs/ip/open-shortest-path-first-ospf/13685-13.html>

NEW QUESTION 66

Which real time debug should an administrator enable to troubleshoot RADIUS authentication problems?

- A. Diagnose debug application radius -1.
- B. Diagnose debug application fnbamd -1.
- C. Diagnose authd console -log enable.
- D. Diagnose radius console -log enable.

Answer: B

Explanation:

<https://kb.fortinet.com/kb/documentLink.do?externalID=FD32838>

NEW QUESTION 71

Examine the output from the BGP real time debug shown in the exhibit, then the answer the question below:

Which statements are true regarding the output in the exhibit? (Choose two.)

- A. BGP peers have successfully interchanged Open and Keepalive messages.
- B. Local BGP peer received a prefix for a default route.
- C. The state of the remote BGP peer is OpenConfirm.
- D. The state of the remote BGP peer will go to Connect after it confirms the received prefixes.

Answer: AB

NEW QUESTION 72

View the exhibit, which contains a session entry, and then answer the question below.

Which statement is correct regarding this session?

- A. It is an ICMP session from 10.1.10.10 to 10.200.1.1.
- B. It is an ICMP session from 10.1.10.10 to 10.200.5.1.
- C. It is a TCP session in ESTABLISHED state from 10.1.10.10 to 10.200.5.1.

D. It is a TCP session in CLOSE_WAIT state from 10.1.10.10 to 10.200.1.1.

Answer: B

NEW QUESTION 75

An administrator has enabled HA session synchronization in a HA cluster with two members. Which flag is added to a primary unit's session to indicate that it has been synchronized to the secondary unit?

- A. indir.
- B. dirty.
- C. synced
- D. nds.

Answer: C

Explanation:

The synced sessions have the 'synced' flag. The command 'diag sys session list' can be used to see the sessions on the member, with the associated flags.

NEW QUESTION 77

Examine the following routing table and BGP configuration; then answer the question below.

The BGP connection is up, but the local peer is NOT advertising the prefix 192.168.1.0/24. Which configuration change will make the local peer advertise this prefix?

- A. Enable the redistribution of connected routers into BGP.
- B. Enable the redistribution of static routers into BGP.
- C. Disable the setting network-import-check.
- D. Enable the setting ebgp-multipath.

Answer: C

NEW QUESTION 82

Examine the output of the 'diagnose debug rating' command shown in the exhibit; then answer the question below.

Which statement are true regarding the output in the exhibit? (Choose two.)

- A. There are three FortiGuard servers that are not responding to the queries sent by the FortiGate.
- B. The TZ value represents the delta between each FortiGuard server's time zone and the FortiGate's time zone.
- C. FortiGate will send the FortiGuard queries to the server with highest weight.
- D. A server's round trip delay (RTT) is not used to calculate its weight.

Answer: BC

NEW QUESTION 86

View the exhibit, which contains the partial output of a diagnose command, and then answer the question below.

Based on the output, which of the following statements is correct?

- A. Anti-reply is enabled.
- B. DPD is disabled.
- C. Quick mode selectors are disabled.
- D. Remote gateway IP is 10.200.5.1.

Answer: A

NEW QUESTION 88

An administrator has configured two FortiGate devices for an HA cluster. While testing the HA failover, the administrator noticed that some of the switches in the network continue to send traffic to the former primary unit. The administrator decides to enable the setting link-failed-signal to fix the problem. Which statement is correct regarding this command?

- A. Forces the former primary device to shut down all its non-heartbeat interfaces for one second while the failover occurs.
- B. Sends an ARP packet to all connected devices, indicating that the HA virtual MAC address is reachable through a new master after a failover.
- C. Sends a link failed signal to all connected devices.
- D. Disables all the non-heartbeat interfaces in all the HA members for two seconds after a failover.

Answer: A

NEW QUESTION 89

An administrator is running the following sniffer in a FortiGate: diagnose sniffer packet any "host 10.0.2.10" 2
What information is included in the output of the sniffer? (Choose two.)

- A. Ethernet headers.
- B. IP payload.
- C. IP headers.
- D. Port names.

Answer: BC

Explanation:

<https://kb.fortinet.com/kb/documentLink.do?externalID=11186>

NEW QUESTION 90

Examine the following partial outputs from two routing debug commands; then answer the question below.

```
# get router info kernel
```

```
tab=254 vf=0 scope=0type=1 proto=11 prio=0 0.0.0.0/0.0.0.0/0->0.0.0.0/0 pref=0.0.0.0 gwy=10.200.1.254 dev=2(port1)
```

```
tab=254 vf=0 scope=0type=1 proto=11 prio=10 0.0.0.0/0.0.0.0/0->0.0.0.0/0 pref=0.0.0.0 gwy=10.200.2.254 dev=3(port2)
```

```
tab=254 vf=0 scope=253type=1 proto=2 prio=0 0.0.0.0/0.0.0.0/->10.0.1.0/24 pref=10.0.1.254 gwy=0.0.0.0 dev=4(port3)
```

```
# get router info routing-table all s*0.0.0.0/0 [10/0] via 10.200.1.254, port1 [10/0] via 10.200.2.254, port2, [10/0] d0.0.1.0/24 is directly connected, port3  
d0.200.1.0/24 is directly connected, port1 d0.200.2.0/24 is directly connected, port2
```

Which outbound interface or interfaces will be used by this FortiGate to route web traffic from internal users to the Internet?

- A. port1
- B. port2.
- C. Both port1 and port2.
- D. port3.

Answer: B

NEW QUESTION 94

.....

Thank You for Trying Our Product

We offer two products:

1st - We have Practice Tests Software with Actual Exam Questions

2nd - Questions and Answers in PDF Format

NSE7_EFW-6.4 Practice Exam Features:

- * NSE7_EFW-6.4 Questions and Answers Updated Frequently
- * NSE7_EFW-6.4 Practice Questions Verified by Expert Senior Certified Staff
- * NSE7_EFW-6.4 Most Realistic Questions that Guarantee you a Pass on Your FirstTry
- * NSE7_EFW-6.4 Practice Test Questions in Multiple Choice Formats and Updatesfor 1 Year

100% Actual & Verified — Instant Download, Please Click
[Order The NSE7_EFW-6.4 Practice Test Here](#)