

NSE7_EFW-7.0 Dumps

Fortinet NSE 7 - Enterprise Firewall 7.0

https://www.certleader.com/NSE7_EFW-7.0-dumps.html



NEW QUESTION 1

Refer to the exhibit, which contains partial outputs from two routing debug commands.

```
FortiGate # get router into routing-table database
S 0.0.0.0/0 [20/0] via 100.64.2.254, port2, [10/0]
S *>0.0.0.0/0 [10/0] via 100.64.1.254, port1

FortiGate # get router info routing-table all
S* 0.0.0.0/0 [10/0] via 100.64.1.254, port1
```

Why is the port2 default route not in the second command's output?

- A. It has a higher priority value than the default route using port1.
- B. It is disabled in the FortiGate configuration.
- C. It has a lower priority value than the default route using port1.
- D. It has a higher distance than the default route using port1.

Answer: D

NEW QUESTION 2

A FortiGate device has the following LDAP configuration:

```
config user ldap
  edit "WindowsLDAP"
    set server "10.0.1.10"
    set cnid "cn"
    set dn "cn=user, dc=trainingAD, dc=training, dc=lab"
    set type regular
    set username "cn=administrator, cn=users, dc=trainingAD,
dc=training, dc=lab"
    set password xxxxx
  next
end
```

The LDAP user student cannot authenticate. The exhibit shows the output of the authentication real time debug while testing the student account:

```
#diagnose debug application fnbamd -1
#diagnose debug enable
#diagnose test authserver ldap WindowsLDAP student password
fnbamd_fsm.c[1819] handle_req-Rcvd auth req 4 for student in WindowsLDAP
opt=27 prot=0
fnbamd_fsm.c[336] compose_group_list_from_req_Group 'WindowsLDAP'
fnbamd_pop3.c[573] fnbamd_pop3_start-student
fnbamd_cfg.c[932] fnbamd_cfg-get_ldap_ist_by_server-Loading LDAP server
'WindowsLDAP'
fnbamd_ldap.c[992] resolve_ldap_FQDN-Resolved address 10.0.1.10, result 10.0.1.10
fnbamd_fsm.c[428] create_auth_session-Total 1 server(s) to try
fnbamd_ldap.c[1700] fnbamd_ldap_get_result-Error in ldap result: 49
(Invalid credentials)
fnbamd_ldap.c[2028] fnbamd_ldap_get_result-Auth denied
fnbamd_auth.c[2188] fnbamd_auth_poll_ldap-Result for ldap svr 10.0.1.10 is denied
fnbamd_comm.c[169] fnbamd_comm_send_result-Sending result 1 for req 4
fnbamd_fsm.c[568] destroy_auth_session-delete session 4
authenticate 'student' against 'WindowsLDAP' failed!
```

Based on the above output, what FortiGate LDAP settings must the administrator check? (Choose two.)

- A. cnid.
- B. username.
- C. password.
- D. dn.

Answer: BC

Explanation:

<https://kb.fortinet.com/kb/viewContent.do?externalId=13141>

NEW QUESTION 3

Refer to the exhibit, which contains the output of get system ha status. Which two statements about the output are true? (Choose two.)

```

NGFW-1 # get system ha status
HA Health Status: OK
Model: FortiGate-VM64
Mode: HA A-P
Group: 2
Debug: 0
Cluster Uptime: 0 days 4:23:19
Cluster state change time: 2019-01-25 10:19:46
Master selected using:
  <2019/01/25 10:19:46> FGVM010000077649 is selected as the master because it has the largest value
of override priority.
  <2019/01/25 10:19:40> FGVM010000077649 is selected as the master because it's the only member in
the cluster.
ses_pickup: disable
override: enable
Configuration Status:
  FGVM010000077649 (updated 1 seconds ago): in-sync
  FGVM010000077650 (updated 0 seconds ago): out-of-sync
System Usage stats:
  FGVM010000077649 (updated 1 seconds ago):
    sessions=27, average-cpu-user/nice/system/idle=1%/0%/0%/99%, memory=56%
  FGVM010000077650 (updated 0 seconds ago):
    sessions=2, average-cpu-user/nice/system/idle=1%/0%/0%/99%, memory=57%
HBDEV stats:
  FGVM010000077649 (updated 1 seconds ago):
    port7: physical/10000full, up, rx-bytes/packets/dropped/errors=63817615/202024/0/0, tx=
71110281/121109/0/0
  FGVM010000077650 (updated 0 seconds ago):
    port7: physical/10000full, up, rx-bytes/packets/dropped/errors=79469596/122024/0/0, tx=
30877890/107878/0/0
Master: NGFW-1      , FGVM010000077649, cluster index = 1
Slave : NGFW-2      , FGVM010000077650, cluster index = 0
number of vcluster: 1
vcluster 1: work 169.254.0.2
Master: FGVM010000077649, operating cluster index = 0
Slave : FGVM010000077650, operating cluster index = 1

```

- A. The slave configuration is synchronized with the master.
- B. port7 is used as the HA heartbeat on all devices in the cluster.
- C. Primary is selected based on the priority configured under config system ha.
- D. The HA management IP is 169.254.0.2.

Answer: BC

NEW QUESTION 4

What does the dirty flag mean in a FortiGate session?

- A. Traffic has been blocked by the antivirus inspection.
- B. The next packet must be re-evaluated against the firewall policies.
- C. The session must be removed from the former primary unit after an HA failover.
- D. Traffic has been identified as from an application that is not allowed.

Answer: B

Explanation:

<https://kb.fortinet.com/kb/viewContent.do?externalId=FD40119&sliceId=1>

NEW QUESTION 5

What is the purpose of an internal segmentation firewall (ISFW)?

- A. It inspects incoming traffic to protect services in the corporate DMZ.
- B. It is the first line of defense at the network perimeter.
- C. It splits the network into multiple security segments to minimize the impact of breaches.
- D. It is an all-in-one security appliance that is placed at remote sites to extend the enterprise network.

Answer: C

Explanation:

ISFW splits your network into multiple security segments. They serve as a breach containers from attacks that come from inside.

NEW QUESTION 6

Which statements about bulk configuration changes using FortiManager CLI scripts are correct? (Choose two.)

- A. When executed on the Policy Package, ADOM database, changes are applied directly to the managed FortiGate.
- B. When executed on the Device Database, you must use the installation wizard to apply the changes to the managed FortiGate.
- C. When executed on the All FortiGate in ADOM, changes are automatically installed without creating a new revision history.
- D. When executed on the Remote FortiGate directly, administrators do not have the option to review the changes prior to installation.

Answer: BD

Explanation:

CLI scripts can be run in three different ways: Device Database: By default, a script is executed on the device database. It is recommend you run the changes on the device database (default setting), as this allows you to check what configuration changes you will send to the managed device. Once scripts are run on the device database, you can install these changes to a managed device using the installation wizard.
Policy Package, ADOM database: If a script contains changes related to ADOM level objects and policies, you can change the default selection to run on Policy Package, ADOM database and can then be installed using the installation wizard.
Remote FortiGate directly (through CLI): A script can be executed directly on the device and you don't need to install these changes using the installation wizard. As the changes are directly installed on the managed device, no option is provided to verify and check the configuration changes through FortiManager prior to executing it.

NEW QUESTION 7

Refer to the exhibit, which contains partial output from an IKE real-time debug.

```
ike 0: comes 10.0.0.2:500->10.0.0.1:500, ifindex=7. . .
ike 0: IKEv2 exchange=Aggressive id=a2fbd6bb6394401a/06b89c022d4df682 len=426
ike 0: Remotesite:3: initiator: aggressive mode get 1st response. . .
ike 0: Remotesite:3: VID DPD AFCAD71368A1F1C96B8696FC77570100
ike 0: Remotesite:3: DPD negotiated
ike 0: Remotesite:3: VID FORTIGATE 8299031757A36082C6A621DE00000000
ike 0: Remotesite:3: peer is FortiGate/PortiOS (v0 b0)
ike 0: Remotesite:3: VID FRAGMENTATION 4048B7D56EBCE88525E7DE7F00D6C2D3
ike 0: Remotesite:3: VID FRAGMENTATION 4048B7D56EBCE88525E7DE7F00D6C2D3C0000000
ike 0: Remotesite:3: received peer identifier FQDN 'remote'
ike 0: Remotesite:3: negotiation result
ike 0: Remotesite:3: proposal id = 1:
ike 0: Remotesite:3:   protocol id = ISAKMP:
ike 0: Remotesite:3:   trans_id = KEY_IKE.
ike 0: Remotesite:3:   encapsulation = IKE/none.
ike 0: Remotesite:3:   type=OAKLEY_ENCRYPT_ALG, val=AES_CBC, key-len=128
ike 0: Remotesite:3:   type=OAKLEY_HASH_ALG, val=SHA.
ike 0: Remotesite:3:   type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0: Remotesite:3:   type=OAKLEY_GROUP, val=MODP1024.
ike 0: Remotesite:3: ISAKMP SA lifetime=86400
ike 0: Remotesite:3: NAT-T unavailable
ike 0: Remotesite:3: ISAKMP SA a2fbd6bb6394401a/06b89c022d4df682 key
16:39915120ED73ED73E520787C801DE3678916
ike 0: Remotesite:3: PSK authentication succeeded
ike 0: Remotesite:3: authentication OK
ike 0: Remotesite:3: add INITIAL-CONTACT
ike 0: Remotesite:3: enc
A2FBD6BB6394401A06B89C022D4DF6820810040100000000000000500B000018882A07BE09026CA8B2
ike 0: Remotesite:3: out
A2FBD6BB6394401A06B89C022D4DF68208100401000000000000005C64D5CBA90B873F150CB8B5CC2A
ike 0: Remotesite:3: sent IKE msg (agg_i2send): 10.0.0.1:500->10.0.0.2:500, len=140,
id=a2fbd6bb6394401a/
ike 0: Remotesite:3: established IKE SA a2fbd6bb6394401a/06b89c022d4df682
```


Which two statements about this debug output are correct? (Choose two.)

- A. The remote gateway IP address is 10.0.0.1.
- B. The initiator provided remote as its IPsec peer ID.
- C. It shows a phase 1 negotiation.
- D. The negotiation is using AES128 encryption with CBC hash.

Answer: BC

NEW QUESTION 8

Exhibits:



```

now router bgp
router bgp
  as 65100
  router-id 172.16.1.1
fig neighbor-group
  edit "advpn"
    set remote-as 65100

    set route-reflector-client disable
  next

fig neighbor-range
  edit 1
    set prefix 172.16.1.0 255.255.255.0
    set neighbor-group "advpn"
  next

```

Refer to the exhibits, which contain the network topology and BGP configuration for a hub.

An administrator is trying to configure ADVPN with a hub-spoke VPN setup using iBGP. All the VPNs are up and connected to the hub. The hub is receiving route information from both spokes over iBGP; however, the spokes are not receiving route information from each other.

What change must the administrator make to the hub BGP configuration so that the routes learned by one spoke are forwarded to the other spokes?

- A. Configure an individual neighbor and remove neighbor-range configuration.
- B. Configure the hub as a route reflector client.
- C. Change the router id to 10.1.0.254.
- D. Make the configuration of remote-as different from the configuration of local-as.

Answer: B

NEW QUESTION 9

Which of the following conditions must be met for a static route to be active in the routing table? (Choose three.)

- A. The next-hop IP address is up.
- B. There is no other route, to the same destination, with a higher distance.
- C. The link health monitor (if configured) is up.
- D. The next-hop IP address belongs to one of the outgoing interface subnets.
- E. The outgoing interface is up.

Answer: CDE

Explanation:

A configured static route only goes to routing table from routing database when all the following are met :

- > The outgoing interface is up
- > There is no other matching route with a lower distance
- > The link health monitor (if configured) is successful
- > The next-hop IP address belongs to one of the outgoing interface subnets

NEW QUESTION 10

Examine the output of the 'diagnose sys session list expectation' command shown in the exhibit; then answer the question below.

```

#diagnose sys session list expectation

session info: proto= proto_state=0 0 duration=3 expire=26 timeout=3600
flags=00000000
sockflag=00000000 sockport=0 av_idx=0 use=39
origin-shaper=
reply-shaper=
per-ip_shaper=
ha_id=0 policy_dir=1 tunnel=
state=new complex
statistic (bytes/packets/allow_err): org=0/0/0 reply=0/0/0 tuples=2
origin-> sink: org pre-> post, reply pre->post dev=2->4/4->2
gwy=10.0.1.10/10.200.1.254
hook=pre dir=org act=dnat 10.171.121.38:0-> 10.200.1.1: 60426
(10.0.1.10: 50365)
hook= pre dir=org act=noop 0.0.0.0:0-> 0.0.0.0:0 (0.0.0.0:0)
pos/(before, after) 0/(0,0), 0/(0,0)
misc=0 policy_id=1 auth_info=0 chk_client_info=0 vd=0
serial=000000e9 tos=ff/ff ips_view=0 app_list=0 app=0
dd type=0 dd_mode=0

```

Which statement is true regarding the session in the exhibit?

- A. It was created by the FortiGate kernel to allow push updates from FortiGuard.
- B. It is for management traffic terminating at the FortiGate.
- C. It is for traffic originated from the FortiGate.
- D. It was created by a session helper or ALG.

Answer: D

NEW QUESTION 10

An administrator cannot connect to the GUI of a FortiGate unit with the IP address 10.0.1.254. The administrator runs the debug flow while attempting the connection using HTTP. The output of the debug flow is shown in the exhibit:

```
# diagnose debug flow filter port 80
# diagnose debug flow trace start 5
# diagnose debug enable

id=20085 trace_id=5 msg="vd-root received a packet(proto=6,
10.0.1.10:57459->10.0.1.254:80) from port3. flag [S], seq 3190430861, ack
0, win 8192"
id=20085 trace_id=5 msg="allocate a new session-0000008c"
id=20085 trace_id=5 msg="iprope_in_check() check failed on policy 0, drop"
```

Based on the error displayed by the debug flow, which are valid reasons for this problem? (Choose two.)

- A. HTTP administrative access is disabled in the FortiGate interface with the IP address 10.0.1.254.
- B. Redirection of HTTP to HTTPS administrative access is disabled.
- C. HTTP administrative access is configured with a port number different than 80.
- D. The packet is denied because of reverse path forwarding check.

Answer: AC

NEW QUESTION 12

Which the following events can trigger the election of a new primary unit in a HA cluster? (Choose two.)

- A. Primary unit stops sending HA heartbeat keepalives.
- B. The FortiGuard license for the primary unit is updated.
- C. One of the monitored interfaces in the primary unit is disconnected.
- D. A secondary unit is removed from the HA cluster.

Answer: AC

NEW QUESTION 13

A FortiGate has two default routes:

```
config router static
  edit 1
    set gateway 10.200.1.254
    set priority 5
    set device "port1"
  next
  edit 2
    set gateway 10.200.2.254
    set priority 10
    set device "port2"
  next
end
```

All Internet traffic is currently using port1. The exhibit shows partial information for one sample session of Internet traffic from an internal user:

```
# diagnose sys session list
Session info: proto=6 proto_state=01 duration =17 expire=7 timeout=3600
flags= 00000000 sockflag=00000000 sockport=0 av idx=0 use=3
ha_id=0 policy_dir=0 tunnel=/
state=may_dirty none app_ntf
statistic (bytes/packets/allow_err): org=575/7/1 reply=23367/19/1 tuples=2
origin->sink: org pre->post, reply pre->post dev=4->2/2->4
gwy=10.200.1.254/10.0.1.10
hook=post dir=org act=snat 10.0.1.10:64907-
>54.239.158.170:80(10.200.1.1:64907)
hook=pre dir=reply act=dnat 54.239.158.170:80-
>10.200.1.1:64907(10.0.1.10:64907)
pos/(before, after) 0/(0,0), 0/(0,0)
misc=0 policy_id=1 auth_info=0 chk_client_info=0 vd=0
serial=00000294 tos=ff/ff ips_view=0 app_list=0 app=0
dd_type=0 dd_mode=0
```

What would happen with the traffic matching the above session if the priority on the first default route (IDd1) were changed from 5 to 20?

- A. The session would be deleted, and the client would need to start a new session.
- B. The session would remain in the session table, and its traffic would start to egress from port2.
- C. The session would remain in the session table, but its traffic would now egress from both port1 and port2.
- D. The session would remain in the session table, and its traffic would still egress from port1.

Answer: D

NEW QUESTION 18

An administrator has enabled HA session synchronization in a HA cluster with two members. Which flag is added to a primary unit's session to indicate that it has been synchronized to the secondary unit?

- A. redir.
- B. dirty.
- C. synced
- D. nds.

Answer: C

Explanation:

The synced sessions have the 'synced' flag. The command 'diag sys session list' can be used to see the sessions on the member, with the associated flags.

NEW QUESTION 22

Which statement about memory conserve mode is true?

- A. A FortiGate exits conserve mode when the configured memory use threshold reaches yellow.
- B. A FortiGate starts dropping all the new and old sessions when the configured memory use threshold reaches extreme.
- C. A FortiGate starts dropping new sessions when the configured memory use threshold reaches red
- D. A FortiGate enters conserve mode when the configured memory use threshold reaches red

Answer: D

NEW QUESTION 25

Which two tasks are automated using the Install Wizard on FortiManager? (Choose two.)

- A. Preview pending configuration changes for managed devices.
- B. Add devices to FortiManager.
- C. Import policy packages from managed devices.
- D. Install configuration changes to managed devices.
- E. Import interface mappings from managed devices.

Answer: AD

Explanation:

https://help.fortinet.com/fmgr/50hlp/56/5-6-2/FortiManager_Admin_Guide/1000_Device%20Manager/1200_ins

There are 4 main wizards: Add Device: is used to add devices to central management and import their configurations.

Install: is used to install configuration changes from Device Manager or Policies & Objects to the managed devices. It allows you to preview the changes and, if the administrator doesn't agree with the changes, cancel and modify them.

Import policy: is used to import interface mapping, policy database, and objects associated with the managed devices into a policy package under the Policy & Object tab. It runs with the Add Device wizard by default and may be run at any time from the managed device list.

Re-install policy: is used to perform a quick install of the policy package. It doesn't give the ability to preview the changes that will be installed to the managed device.

NEW QUESTION 26

Refer to exhibit, which contains the output of a BGP debug command.

```

FGT # get router info bgp summary
BGP router identifier 10.200.1.1, local AS number 655
BGP table version is 2
1 BGP AS-PATH entries
0 BGP community entries

Neighbor      V   AS      MsgRcvd  MsgSent   TblVer
10.200.3.1    4 65501    92       1756      0

Total number of neighbors 1
    
```

Which statement explains why the state of the 10.200.3.1 peer is Connect?

- A. The local router is receiving BGP keepalives from the remote peer, but the local peer has not received the OpenConfirm yet.
- B. The TCP session to 10.200.3.1 has not completed the three-way handshake.
- C. The local router is receiving the BGP keepalives from the peer, but it has not received a BGP prefix yet.
- D. The local router has received the BGP prefixes from the remote peer.

Answer: B

Explanation:

BGP neighbor states and how they change: • Idle: Initial state • Connect: Waiting for a successful three-way TCP connection • Active: Unable to establish the TCP session • OpenSent: Waiting for an OPEN message from the peer • OpenConfirm: Waiting for the keepalive message from the peer • Established: Peers have successfully exchanged OPEN and keepalive messages

NEW QUESTION 30

Examine the following partial output from a sniffer command; then answer the question below.

```
# diagnose sniff packet any 'icmp' 4
interfaces= [any]
filters = [icmp]
2.101199 wan2 in 192.168.1.110-> 4.2.2.2: icmp: echo request
2.101400 wan1 out 172.17.87.16-> 4.2.2.2: icmp: echo request
.....
2.123500 wan2 out 4.2.2.2-> 192.168.1.110: icmp: echo reply
244 packets received by filter
5 packets dropped by kernel
```

What is the meaning of the packets dropped counter at the end of the sniffer?

- A. Number of packets that didn't match the sniffer filter.
- B. Number of total packets dropped by the FortiGate.
- C. Number of packets that matched the sniffer filter and were dropped by the FortiGate.
- D. Number of packets that matched the sniffer filter but could not be captured by the sniffer.

Answer: D

Explanation:

<https://kb.fortinet.com/kb/documentLink.do?externalID=11655>

NEW QUESTION 33

An administrator has configured two FortiGate devices for an HA cluster. While testing HA failover, the administrator notices that some of the switches in the network continue to send traffic to the former primary device. The administrator decides to enable the setting link-failed-signal to fix the problem. Which statement about this setting is true?

- A. It sends an ARP packet to all connected devices, indicating that the HA virtual MAC address is reachable through a new master after a failover.
- B. It sends a link failed signal to all connected devices.
- C. It disabled all the non-heartbeat interfaces in all HA members for two seconds after a failover.
- D. It forces the former primary device to shut down all its non-heartbeat interfaces for one second, while the failover occurs.

Answer: D

NEW QUESTION 34

View the exhibit, which contains the partial output of an IKE real-time debug, and then answer the question below.

```
ike 0:c49e59846861b0f6/0000000000000000:278: responder: main mode get 1st message...
ike 0:c49e59846861b0f6/0000000000000000:278: incoming proposal:
ike 0:c49e59846861b0f6/0000000000000000:278: proposal id = 0:
ike 0:c49e59846861b0f6/0000000000000000:278: protocol id = ISAKMP:
ike 0:c49e59846861b0f6/0000000000000000:278: trans_id = KEY_IKE.
ike 0:c49e59846861b0f6/0000000000000000:278: encapsulation = IKE/none
ike 0:c49e59846861b0f6/0000000000000000:278: type=OAKLEY_ENCRYPT_ALG, val=3DES_CBC.
ike 0:c49e59846861b0f6/0000000000000000:278: type=OAKLEY_HASH_ALG, val=SHA2_256.
ike 0:c49e59846861b0f6/0000000000000000:278: type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:c49e59846861b0f6/0000000000000000:278: type=OAKLEY_GROUP, val=MODP2048.
ike 0:c49e59846861b0f6/0000000000000000:278: ISAKMP SA lifetime=86400
...
ike 0:c49e59846861b0f6/0000000000000000:278: my proposal, gw VPN:
ike 0:c49e59846861b0f6/0000000000000000:278: proposal id = 1:
ike 0:c49e59846861b0f6/0000000000000000:278: protocol id = ISAKMP:
ike 0:c49e59846861b0f6/0000000000000000:278: trans_id = KEY_IKE.
ike 0:c49e59846861b0f6/0000000000000000:278: encapsulation = IKE/none
ike 0:c49e59846861b0f6/0000000000000000:278: type=OAKLEY_ENCRYPT_ALG, val=AES_CBC,
key-len=256
ike 0:c49e59846861b0f6/0000000000000000:278: type=OAKLEY_HASH_ALG, val=SHA2_256.
ike 0:c49e59846861b0f6/0000000000000000:278: type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:c49e59846861b0f6/0000000000000000:278: type=OAKLEY_GROUP, val=MODP2048.
ike 0:c49e59846861b0f6/0000000000000000:278: ISAKMP SA lifetime=86400
...
ike 0:c49e59846861b0f6/0000000000000000:278: negotiation failure
ike Negotiate ISAKMP SA Error: ike 0:c49e59846861b0f6/0000000000000000:278:
proposal chosen
...
```

Why didn't the tunnel come up?

- A. The pre-shared keys do not match.
- B. The remote gateway's phase 2 configuration does not match the local gateway's phase 2 configuration.
- C. The remote gateway's phase 1 configuration does not match the local gateway's phase 1 configuration.
- D. The remote gateway is using aggressive mode and the local gateway is configured to use man mode.

Answer: C

NEW QUESTION 35

An administrator has configured a FortiGate device with two VDOMs: root and internal. The administrator has also created and inter-VDOM link that connects both VDOMs. The objective is to have each VDOM advertise some routes to the other VDOM via OSPF through the inter-VDOM link. What OSPF configuration settings must match in both VDOMs to have the OSPF adjacency successfully forming? (Choose three.)

- A. Router ID.
- B. OSPF interface area.
- C. OSPF interface cost.

- D. OSPF interface MTU.
- E. Interface subnet mask.

Answer: BDE

NEW QUESTION 36

When using the SSL certificate inspection method for HTTPS traffic, how does FortiGate filter web requests when the browser client does not provide the server name indication (SNI) extension?

- A. FortiGate uses CN information from the Subject field in the server's certificate.
- B. FortiGate switches to the full SSL inspection method to decrypt the data.
- C. FortiGate blocks the request without any further inspection.
- D. FortiGate uses the requested URL from the user's web browser.

Answer: A

NEW QUESTION 40

A FortiGate's port1 is connected to a private network. Its port2 is connected to the Internet. Explicit web proxy is enabled in port1 and only explicit web proxy users can access the Internet. Web cache is NOT enabled. An internal web proxy user is downloading a file from the Internet via HTTP. Which statements are true regarding the two entries in the FortiGate session table related with this traffic? (Choose two.)

- A. Both session have the local flag on.
- B. The destination IP addresses of both sessions are IP addresses assigned to FortiGate's interfaces.
- C. One session has the proxy flag on, the other one does not.
- D. One of the sessions has the IP address of port2 as the source IP address.

Answer: AD

NEW QUESTION 45

Refer to the exhibit, which contains the debug output of diagnose dvm device list.

```

FMG-VM64# diagnose dvm device list
There are currently 1 devices/vdoms managed:
TYPE      OID      SN      HA      IP      NAME      ADOM      IPS      FIRMWARE
fmg/      217     FGVM01... -    10.200.1.1 Local-FortiGate My_ADOM 15.0.0831 6.0 MR4 (1579)
faz enabled
                                     (regular)
|- STATUS: db: modified; conf: in sync; cond: pending; dm: retrieved; conn: up

|- vdom: [3] root flags:0 adom:My_ADOM pkg: [imported] Local-FortiGate_root
    
```

Which two statements about the output shown in the exhibit are correct? (Choose two.)

- A. ADOMs are disabled on the FortiManager
- B. The FortiGate configuration is in sync with latest running revision history.
- C. There are pending device-level changes yet to be installed on Local-FortiGate.
- D. The policy package has been modified for Local-FortiGate.

Answer: BC

NEW QUESTION 46

A FortiGate device has the following LDAP configuration:

```

config user ldap
  edit "WindowsLDAP"
    set server "10.0.1.10"
    set cnid "cn"
    set dn "cn=Users, dc=trainingAD, dc=training, dc=lab"
    set type regular
    set username "dc=trainingAD, dc=training, dc=lab"
    set password xxxxxxxx
  next
end
    
```

The administrator executed the 'dsquery' command in the Windows LDAP server 10.0.1.10, and got the following output:

>dsquery user -samid administrator

"CN=Administrator, CN=Users, DC=trainingAD, DC=training, DC=lab" Based on the output, what FortiGate LDAP setting is configured incorrectly?

- A. cnid.
- B. username.
- C. password.
- D. dn.

Answer: B

Explanation:

<https://kb.fortinet.com/kb/viewContent.do?externalId=FD37516>

NEW QUESTION 48

An administrator has configured a dial-up IPsec VPN with one phase 2, extended authentication (XAuth) and IKE mode configuration. The administrator has also

enabled the IKE real time debug:

diagnose debug application ike-1 diagnose debug enable

In which order is each step and phase displayed in the debug output each time a new dial-up user is connecting to the VPN?

- A. Phase1; IKE mode configuration; XAuth; phase 2.
- B. Phase1; XAuth; IKE mode configuration; phase2.
- C. Phase1; XAuth; phase 2; IKE mode configuration.
- D. Phase1; IKE mode configuration; phase 2; XAuth.

Answer: B

Explanation:

https://help.fortinet.com/fo50hlp/54/Content/FortiOS/fortigate-ipsecvpn-54/IPsec_VPN_Concepts/IKE_Packet

NEW QUESTION 52

What global configuration setting changes the behavior for content-inspected traffic while FortiGate is in system conserve mode?

- A. av-failopen
- B. mem-failopen
- C. utm-failopen
- D. ips-failopen

Answer: A

Explanation:

https://help.fortinet.com/fo50hlp/54/Content/FortiOS/fortigate-security-profiles-54/Other_Profile_Consideratio

NEW QUESTION 56

Examine the following partial output from two system debug commands; then answer the question below.

```
# diagnose hardware sysinfo memory
MemTotal: 3092728 kB
MemFree: 1954204 kB
MemShared: 0 kB
Buffers: 284 kB
Cached: 143004 kB
SwapCached: 0 kB
Active: 34092 kB
Inactive: 109256 kB
HighTotal 1179648 kB
HighFree: 853516 kB
LowTotal: 1913080 kB
LowFree: 1100688 kB
SwapTotal: 0 kB
SwapFree: 0 kB
# diagnose hardware sysinfo shm
SHM counter: 285
SHM allocated: 6823936
SHM total: 623452160
concernemode: 0
shm last entered: n/a
system last entered: n/a
SHM FS total: 639725568
SHM FS free: 632614912

SHM FS alloc: 7110656
```

Which of the following statements are true regarding the above outputs? (Choose two.)

- A. The unit is running a 32-bit FortiOS
- B. The unit is in kernel conserve mode
- C. The Cached value is always the Active value plus the Inactive value
- D. Kernel indirectly accesses the low memory (LowTotal) through memory paging

Answer: AC

NEW QUESTION 58

Examine the output of the 'diagnose debug rating' command shown in the exhibit; then answer the question below.

```
# diagnose debug rating
Locale      : english
License     : Contract
Expiration  : Wed Mar 27 17:00:00 20xx
-- Server List (Mon Apr 16 15:32:55 20xx) --
IP          Weight  RTT   Flags  TZ   Packets  Curr Lost  Total Lost
69.195.205.101  10    45    -5     -5   262432   0          846
69.195.205.102  10    46    -5     -5   329072   0          6806
209.222.147.43  10    75    -5     -5   71638    0          275
96.45.33.65    20    71    -8     -8   36875    0          92
208.91.112.196  20    103   DI     -8   34784    0          1070
208.91.112.198  20    107   D      -8   35170    0          1533
80.85.69.41    60    144   0      0    33728    0          120
62.209.40.73   71    226   1      1    33797    0          192
121.111.236.180 150   197   9      9    33754    0          145
69.195.205.103  45    44    F      -5   26410    26226     26227
```

Which statement are true regarding the output in the exhibit? (Choose two.)

- A. There are three FortiGuard servers that are not responding to the queries sent by the FortiGate.
- B. The TZ value represents the delta between each FortiGuard server's time zone and the FortiGate's time zone.
- C. FortiGate will send the FortiGuard queries to the server with highest weight.
- D. A server's round trip delay (RTT) is not used to calculate its weight.

Answer: BC

NEW QUESTION 62

Which of the following statements are true regarding the SIP session helper and the SIP application layer gateway (ALG)? (Choose three.)

- A. SIP session helper runs in the kernel; SIP ALG runs as a user space process.
- B. SIP ALG supports SIP HA failover; SIP helper does not.
- C. SIP ALG supports SIP over IPv6; SIP helper does not.
- D. SIP ALG can create expected sessions for media traffic; SIP helper does not.
- E. SIP helper supports SIP over TCP and UDP; SIP ALG supports only SIP over UDP.

Answer: BCD

NEW QUESTION 67

Examine the following partial outputs from two routing debug commands; then answer the question below.

```
# get router info kernel
tab=254 vf=0 scope=0type=1 proto=11 prio=0 0.0.0.0/0.0.0.0/0->0.0.0.0/0 pref=0.0.0.0 gwy=10.200.1.254 dev=2(port1)
tab=254 vf=0 scope=0type=1 proto=11 prio=10 0.0.0.0/0.0.0.0/0->0.0.0.0/0 pref=0.0.0.0 gwy=10.200.2.254 dev=3(port2)
tab=254 vf=0 scope=253type=1 proto=2 prio=0 0.0.0.0/0.0.0.0/0.->10.0.1.0/24 pref=10.0.1.254 gwy=0.0.0.0 dev=4(port3)
# get router info routing-table all s*0.0.0.0/0 [10/0] via 10.200.1.254, port1 [10/0] via 10.200.2.254, port2, [10/0] dO.0.1.0/24 is directly connected, port3
dO.200.1.0/24 is directly connected, port1 dO.200.2.0/24 is directly connected, port2
```

Which outbound interface or interfaces will be used by this FortiGate to route web traffic from internal users to the Internet?

- A. port1
- B. port2.
- C. Both port1 and port2.
- D. port3.

Answer: B

NEW QUESTION 68

When does a RADIUS server send an Access-Challenge packet?

- A. The server does not have the user credentials yet.
- B. The server requires more information from the user, such as the token code for two-factor authentication.
- C. The user credentials are wrong.
- D. The user account is not found in the server.

Answer: B

NEW QUESTION 70

Examine the partial output from two web filter debug commands; then answer the question below:

```
# diagnose test application urlfilter 3
Domain | IP      DB Ver  T URL
34000000| 34000000  16.40224 P Bhttp://www.fgt99.com/
# get webfilter categories
g07 General Interest - Business:
  34 Finance and Banking
  37 Search Engines and Portals
  43 General Organizations
  49 Business
  50 Information and Computer Security
  51 Government and Legal Organizations
  52 Information Technology
```

Based on the above outputs, which is the FortiGuard web filter category for the web site www.fgt99.com?

- A. Finance and banking
- B. General organization.
- C. Business.
- D. Information technology.

Answer: C

NEW QUESTION 74

Examine the output from the 'diagnose debug authd fssolist' command; then answer the question below.

```
# diagnose debug authd fssolist --FSSO logons-IP: 192.168.3.1 User: STUDENT Groups: TRAININGAD/USERS Workstation: INTERNAL2. TRAINING. LAB The IP address 192.168.3.1 is NOT the one used by the workstation INTERNAL2. TRAINING. LAB. What should the administrator check?
```

- A. The IP address recorded in the logon event for the user STUDENT.
- B. The DNS name resolution for the workstation name INTERNAL2. TRAININ
- C. LAB.
- D. The source IP address of the traffic arriving to the FortiGate from the workstation INTERNAL2.TRAININ
- E. LAB.
- F. The reserve DNS lookup forthe IP address 192.168.3.1.

Answer: C

NEW QUESTION 76

View the exhibit, which contains the output of a diagnose command, and the answer the question below.

```
# diagnose debug rating
Locale      : English
License     : Contract
Expiration  : Thu Sep 28 17:00:00 20XX
-- Server List (Thu APR 19 10:41:32 20XX) --
```

IP	Weight	RTT	Flags	TZ	Packets	Curr Lost	Total Lost
64.26.151.37	10	45		-5	262432	0	846
64.26.151.35	10	46		-5	329072	0	6806
66.117.56.37	10	75		-5	71638	0	275
66.210.95.240	20	71		-8	36875	0	92
209.222.147.36	20	103	DI	-8	34784	0	1070
208.91.112.194	20	107	D	-8	35170	0	1533
96.45.33.65	60	144		0	33728	0	120
80.85.69.41	71	226		1	33797	0	192
62.209.40.74	150	97		9	33754	0	145
121.111.236.179	45	44	F	-5	26410	26226	26227

Which statements are true regarding the Weight value?

- A. Its initial value is calculated based on the round trip delay (RTT).
- B. Its initial value is statically set to 10.
- C. Its value is incremented with each packet lost.
- D. It determines which FortiGuard server is used for license validation.

Answer: C

NEW QUESTION 80

An administrator has configured the following CLI script on FortiManager, which failed to apply any changes to the managed device after being executed.

```
# conf rout stat
#   edit 0
#   set gateway 10.20.121.2
#   set priority 20
#   set device "wan1"
#   next
# end
```

Why didn't the script make any changes to the managed device?

- A. Commands that start with the # sign are not executed.
- B. CLI scripts will add objects only if they are referenced by policies.
- C. Incomplete commands are ignored in CLI scripts.
- D. Static routes can only be added using TCL scripts.

Answer: A

Explanation:

https://help.fortinet.com/fmgr/50hlp/56/5-6-2/FortiManager_Admin_Guide/1000_Device%20Manager/2400_Sc

A sequence of FortiGate CLI commands, as you would type them at the command line. A comment line starts with the number sign (#). A comment line will not be executed.

NEW QUESTION 81

Refer to the exhibit, which contains partial output from an IKE real-time debug.

```
ike 0:H2S_0_1:1249: notify msg received: SHORTCUT-QUERY
ike 0:H2S_0_1:  recv shortcut-query 12594932268010586978 4384dd592d62cd52/0000000000000000 100.64.3.1
10.1.1.254->10.1.2.254 psk 64 ppk 0 ttl 32 nat 0 ver 1 mode 0
ike 0:H2S_0: iif 13 10.1.1.254->10.1.2.254 route lookup oif 13
ike 0:H2S_0_0: forward shortcut-query 12594932268010586978 4384dd592d62cd52/0000000000000000
100.64.3.1 10.1.1.254->10.1.2.254 psk 64 ppk 0 ttl 31 ver 1 mode 0, ext-ma
ike 0:H2S_0_0:1248: sent IKE msg (SHORTCUT-QUERY): 100.64.1.1:500->100.64.5.1:500, len=236,
id=e2beec89f13c7074/06a73dfb3a5d3b54:340a645c
ike 0: comes 100.64.5.1:500->100.64.1.1:500, ifindex=3. . .
ike 0: IKEv1 exchange=Informational id=e2beec89f13c7074/06a73dfb3a5d3b5d:26254ae9 len=236
ike 0:H2S_0_0:1248: notify msg received: SHORTCUT-REPLY
ike 0:H2S_0_0:  recv shortcut-reply 12594932268010586978 4384dd592d62cd52/89bf040f5f7408c0 100.64.5.1
to 10.1.1.254 psk 64 ppk 0 ver 1 mode 0 ext-mapping 100.64.3.1:500
ike 0:H2S_0: iif 13.10.1.2.254->10.1.1.254 route lookup oif 13
ike 0:H2S_0_1: forward shortcut-reply 12594932268010586978 4384dd592d62cd52/89bf040f5f7408c0
100.64.5.1 to 10.1.1.254 psk 64 ppk 0 ttl 31 ver 1 mode 0 ext-mapping 100.
```

Based on the debug output, which phase 1 setting is enabled in the configuration of this VPN?

- A. auto-discovery-shortcut
- B. auto-discovery-forwarder
- C. auto-discovery-sender
- D. auto-discovery-receiver

Answer: D

NEW QUESTION 83

View the exhibit, which contains the output of a web diagnose command, and then answer the question below.

```
# diagnose webfilter fortiguard statistics list
```

Raring Statistics:

```
=====
DNS filures           : 273
DNS lookups           : 280
Data send failures    : 0
Data read failures    : 0
Wrong package type    : 0
Hash table miss       : 0
Unknown server        : 0
Incorrect CRC         : 0
Proxy requests failures : 0
Request timeout       : 1
Total requests        : 2409
Requests to FortiGuard servers : 1182
Server errored responses : 0
Relayed rating        : 0
Invalid profile       : 0

Allowed              : 1021
Blocked              : 3909
Logged               : 3927
Blocked Errors       : 565
Allowed Errors       : 0
Monitors             : 0
Authenticates        : 0
Warnings             : 18
Ovrd request timeout : 0
Ovrd send failures   : 0
Ovrd read failures   : 0
Ovrd errored responses : 0
...
```

```
# diagnose webfilter fortiguard statistics list
```

Cache Statistics:

```
=====
Maximum memory       : 0
Memory usage         : 0

Nodes                : 0
Leaves               : 0
Prefix nodes         : 0
Exact nodes          : 0

Requests             : 0
Misses               : 0
Hits                 : 0
Prefix hits          : 0
Exact hits           : 0

No cache directives  : 0
Add after prefix     : 0
Invalid DB put       : 0
DB updates           : 0

Percent full         : 0%
Branches             : 0%
Leaves               : 0%
Prefix nodes         : 0%
Exact nodes          : 0%

Miss rate             : 0%
Hit rate              : 0%
Prefix hits          : 0%
Exact hits           : 0%
```

Which one of the following statements explains why the cache statistics are all zeros?

- A. The administrator has reallocated the cache memory to a separate process.
- B. There are no users making web requests.
- C. The FortiGuard web filter cache is disabled in the FortiGate's configuration.
- D. FortiGate is using a flow-based web filter and the cache applies only to proxy-based inspection.

Answer: C

NEW QUESTION 86

Which two statements about OCVPN are true? (Choose two.)

- A. Only root vdom supports OCVPN.
- B. OCVPN supports static and dynamic IPs in WAN interface.
- C. OCVPN offers only Hub-Spoke VPNs.
- D. FortiGate devices under different FortiCare accounts can be used to form OCVPN.

Answer: AB

NEW QUESTION 88

What configuration changes can reduce the memory utilization in a FortiGate? (Choose two.)

- A. Reduce the session time to live.
- B. Increase the TCP session timers.
- C. Increase the FortiGuard cache time to live.
- D. Reduce the maximum file size to inspect.

Answer: AD

NEW QUESTION 91

An administrator has configured two FortiGate devices for an HA cluster. While testing the HA failover, the administrator noticed that some of the switches in the network continue to send traffic to the former primary unit. The administrator decides to enable the setting link-failed-signal to fix the problem. Which statement is correct regarding this command?

- A. Forces the former primary device to shut down all its non-heartbeat interfaces for one second while the failover occurs.
- B. Sends an ARP packet to all connected devices, indicating that the HA virtual MAC address is reachable through a new master after a failover.
- C. Sends a link failed signal to all connected devices.
- D. Disables all the non-heartbeat interfaces in all the HA members for two seconds after a failover.

Answer: A

NEW QUESTION 92

View the exhibit, which contains the output of a BGP debug command, and then answer the question below.

```
FGT # get router info bgp summary
BGP router identifier 0.0.0.117, local AS number 65117
BGP table version is 104
3 BGP AS-PATH entries
0 BGP community entries

Neighbor      V   AS  MsgRcvd  MsgSent  TblVer  InQ  OutQ   Up/Down    State/PfxRcd
10.125.0.60   4 65060  1698     1756    103    0    0    03:02:49    1
10.127.0.75   4 65075  2206     2250    102    0    0    02:45:55    1
100.64.3.1    4 65501   101      115     0      0    0    never        Active

Total number of neighbors 3
```

Which of the following statements about the exhibit are true? (Choose two.)

- A. The local router's BGP state is Established with the 10.125.0.60 peer.
- B. Since the counters were last reset; the 10.200.3.1 peer has never been down.
- C. The local router has received a total of three BGP prefixes from all peers.
- D. The local router has not established a TCP session with 100.64.3.1.

Answer: AD

NEW QUESTION 95

Refer to the exhibit, which shows a partial routing table.

```
FGT # get router info routing-table all
...
Routing table for VRF=7
C    10.73.9.0/24 is directly connected, port2

Routing table for VRF=12
C    10.1.0.0/24 is directly connected, port3
S    10.10.4.0/24 [10/0] via 10.1.0.100, port3
C    10.64.1.0/24 is directly connected, port1

Routing table for VRF=21
S    10.1.0.0/24 [10/0] via 10.72.3.254, port4
C    10.72.3.0/24 is directly connected, port4
```

Assuming all the appropriate firewall policies are configured, which two pings will FortiGate route? (Choose two.)

- A. Source IP address: 10.1.0.10. Destination IP address: 10.64.1.52
- B. Source IP address: 10.72.3.52. Destination IP address: 10.1.0.254
- C. Source IP address: 10.10.4.24, Destination IP address: 10.72.3.20
- D. Source IP address: 10.73.9.10, Destination IP address: 10.72.3.15

Answer: AB

NEW QUESTION 97

View the exhibit, which contains the output of a diagnose command, and then answer the question below.

```
diagnose sys session list expectation

session info: proto=6 proto_state=00 duration=3 expire=26 timeout=3600 flags=00000000
sockflag=00000000 sockport=0 av_idx=0 use=3
origin-shaper=
reply-shaper=
ha_id=0 policy_dir=1 tunnel=/
state=new complex
statistic(bytes/packets/allow_err): org=0/0/0 reply=0/0/0 tuples=2
orgin->sink: org pre->post, reply pre->post dev=2->4/4->2 gwy=10.0.1.10/10.200.1.254
hook=pre dir-org act=dnat 10.171.122.38:0->10.200.1.1:60426(10.0.1.10:50365)
hook-pre dir-org act=noop 0.0.0.0:0->0.0.0.0:0(0.0.0.0:0)
pos/(before, after) 0/(0,0), 0/(0,0)
misc=0 policy_id=1 auth_info=0 chk_client_info=0 vd=0
serial=000000e9 tos=ff/ff ips_view=0 app_list=0 app=0
dd_type=0 dd_mode=0
```

What statements are correct regarding the output? (Choose two.)

- A. This is an expected session created by a session helper.
- B. Traffic in the original direction (coming from the IP address 10.171.122.38) will be routed to the next-hop IP address 10.0.1.10.
- C. Traffic in the original direction (coming from the IP address 10.171.122.38) will be routed to the next-hop IP address 10.200.1.1.
- D. This is an expected session created by an application control profile.

Answer: AC

NEW QUESTION 98

An administrator added the following Ipsec VPN to a FortiGate configuration:

```
configvpn ipsec phasel -interface edit "RemoteSite"
set type dynamic
```

```
set interface "port1" set mode main
set psksecret ENC LCVkCiK2E2PhVUzZe next
end
config vpn ipsec phase2-interface edit "RemoteSite"
set phasel name "RemoteSite" set proposal 3des-sha256
next end
```

However, the phase 1 negotiation is failing. The administrator executed the IKF real time debug while attempting the Ipsec connection. The output is shown in the exhibit.

```
ike 0: comes 10.200.3.1:500->10.200.1.1:500,ifindex=2...
ike 0: IKEv1 exchange=Identity Protection id=xxx/xxx len=716
ike 0:xxx/xxx:16: responder: main mode get 1st message...
ike 0:xxx/xxx:16: VID RFC 3947 4A131C81070358455C5728F20E95452F
...
ike 0:xxx/xxx:16: negotiation result
ike 0:xxx/xxx:16: proposal id = 1:
ike 0:xxx/xxx:16:   protocol id = ISAKMP:
ike 0:xxx/xxx:16:   trans_id = KEY IKE.
ike 0:xxx/xxx:16:   encapsulation = IKE/none
ike 0:xxx/xxx:16:   type=OAKLEY_ENCRYPT_ALG, val=AES_CBC.
ike 0:xxx/xxx:16:   type=OAKLEY_HASH_ALG, val=SHA2_256.
ike 0:xxx/xxx:16:   type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:xxx/xxx:16:   type=OAKLEY_GROUP, val=MODP2048.
ike 0:xxx/xxx:16: ISAKMP SA lifetime=86400
ike 0:xxx/xxx:16: SA proposal chosen, matched gateway DialUpUsers
...
ike 0:DialUpUsers:16: sent IKE msg (ident_r1send): 10.200.1.1:500->10.200.3.1:500, len
id=xxx/xxx

ike 0: comes 10.200.3.1:500->10.200.1.1:500,ifindex=2...
ike 0: IKEv1 exchange=Identity Protection id=xxx/xxx len=380
ike 0:DialUpUsers:16: responder:main mode get 2nd message...
ike 0:DialUpUsers:16: NAT not detected
ike 0:DialUpUsers:16: sent IKE msg (ident_r2send): 10.200.1.1:500->10.200.3.1:500, len
id=xxx/xxx
ike 0:DialUpUsers:16: ISAKMP SA xxx/xxx key 16:3D33E2EF00BE927701B5C25B05A62415
ike 0: comes 10.200.3.1:500->10.200.1.1:500,ifindex=2...
ike 0: IKEv1 exchange=Identity Protection id=xxx/xxx len=108
ike 0:DialUpUsers:16: responder: main mode get 3rd message...
ike 0:DialUpUsers:16: probable pre-shared secret mismatch
ike 0:DialUpUsers:16: unable to parse msg
```

What is causing the IPsec problem in the phase 1 ?

- A. The incoming IPsec connection is matching the wrong VPN configuration
- B. The phrase-1 mode must be changed to aggressive
- C. The pre-shared key is wrong
- D. NAT-T settings do not match

Answer: C

NEW QUESTION 100

View these partial outputs from two routing debug commands:

```
# get router info kernel
tab=254 vf=0 scope=0 type=1 proto=11 prio=0 0.0.0.0/0.0.0.0/0->0.0.0.0/0 pref=0.0.0.0 gwy=10.200.1.254
dev=2(port1)
tab=254 vf=0 scope=0 type=1 proto=11 prio=0 0.0.0.0/0.0.0.0/0->0.0.0.0/0 pref=0.0.0.0 gwy=10.200.2.254
dev=3(port2)
tab=254 vf=0 scope=253 type=1 proto=2 prio=0 0.0.0.0/0.0.0.0/0->10.0.1.0/24 pref=10.0.1.254 gwy=0.0.0.0
dev=4(port3)
# get router info routing-table all
S* 0.0.0.0/0 [10/0] via 10.200.1.254, port1
   [10/0] via 10.200.2.254, port2, [10/0]
C 10.0.1.0/24 is directly connected, port3
C 10.200.1.0/24 is directly connected, port1
C 10.200.2.0/24 is directly connected, port2
```

Which outbound interface will FortiGate use to route web traffic from internal users to the Internet?

- A. Both port1 and port2
- B. port3
- C. port1
- D. port2

Answer: C

NEW QUESTION 104

View the exhibit, which contains a screenshot of some phase-1 settings, and then answer the question below.

Name	Remote
Comments	Comments
Network	
IP Version	<input checked="" type="radio"/> IPv4 <input type="radio"/> IPv6
Remote Gateway	Static IP address
IP Address	10.0.10.1
Interface	port1
Mode Config	<input type="checkbox"/>
NAT Traversal	<input checked="" type="checkbox"/>
Keepalive Frequency	10
Dead Peer Detection	<input checked="" type="checkbox"/>

The VPN is up, and DPD packets are being exchanged between both IPsec gateways; however, traffic cannot pass through the tunnel. To diagnose, the administrator enters these CLI commands:

```
diagnose vpn ike log-filter src-add4 10.0.10.1
diagnose debug application ike-1
diagnose debug enable
```

However, the IKE real time debug does not show any output. Why?

- A. The debug output shows phases 1 and 2 negotiations onl
- B. Once the tunnel is up, it does not show any more output.
- C. The log-filter setting was set incorrectl
- D. The VPN's traffic does not match this filter.
- E. The debug shows only error message
- F. If there is no output, then the tunnel is operating normally.
- G. The debug output shows phase 1 negotiation onl
- H. After that, the administrator must enable the following real time debug: diagnose debug application ipsec -1.

Answer: B

NEW QUESTION 106

Which two statements about FortiManager is true when it is deployed as a local FDS? (Choose two.)

- A. It caches available firmware updates for unmanaged devices.
- B. It can be configured as an update server, or a rating server, but not both.
- C. It supports rating requests from both managed and unmanaged devices.
- D. It provides VM license validation services.

Answer: CD

NEW QUESTION 111

View the exhibit, which contains the output of a debug command, and then answer the question below.

```
#dia hardware sysinfo shm
SHM counter:          150
SHM allocated:         0
SHM total:           625057792
conserve mode: on - mem
system last entered: Mon Apr 24 16:36:37 2017
sys fd last entered: n/a
SHM FS total:   641236992
SHM FS free:    641208320
SHM FS avail:   641208320
SHM FS alloc:   28672
```

What statement is correct about this FortiGate?

- A. It is currently in system conserve mode because of high CPU usage.
- B. It is currently in FD conserve mode.
- C. It is currently in kernel conserve mode because of high memory usage.
- D. It is currently in system conserve mode because of high memory usage.

Answer: D

NEW QUESTION 114

Which two statements about bulk configuration changes made using FortiManager CLI scripts are correct? (Choose two.)

- A. When run on the Device Database, you must use the installation wizard to apply the changes to the managed FortiGate device.
- B. When run on the Remote FortiGate directly, administrators do not have the option to review the changes prior to installation.
- C. When run on the All FortiGate in ADOM, changes are automatically installed without the creation of a new revision history.
- D. When run on the Policy Package, ADOM database, changes are applied directly to the managed FortiGate device.

Answer: AB

NEW QUESTION 118

Which real time debug should an administrator enable to troubleshoot RADIUS authentication problems?

- A. Diagnose debug application radius -1.
- B. Diagnose debug application fnbamd -1.
- C. Diagnose authd console -log enable.
- D. Diagnose radius console -log enable.

Answer: B

Explanation:

<https://kb.fortinet.com/kb/documentLink.do?externalID=FD32838>

NEW QUESTION 121

View the following FortiGate configuration.

```
config system global
    set snat-route-change disable
end
config router static
    edit 1
        set gateway 10.200.1.254
        set priority 5
        set device "port1"
    next
    edit 2
        set gateway 10.200.2.254
        set priority 10
        set device "port2"
    next
end
```

All traffic to the Internet currently egresses from port1. The exhibit shows partial session information for Internet traffic from a user on the internal network:

```
# diagnose sys session list
session info: proto=6 proto_state+01 duration=17 expire=7 timeout=3600
flags=00000000 sockflag=00000000 sockport=0 av_idx=0 use=3
ha_id=0 policy_dir=0 tunnel=/
state=may_dirty none app_ntf
statistic(bytes/packets/allow_err): org=57555/7/1 reply=23367/19/1 tuples=2
orgin->sink: org pre->post, reply pre->post dev=4->2/2->4
gwy=10.200.1.254/10.0.1.10
hook=post dir=org act=snat 10.0.1.10:64907-
>54.239.158.170:80(10.200.1.1:64907)
hook=pre dir=reply act=dnat 54.239.158.170:80-
>10.200.1.1:64907(10.0.1.10:64907)
pos/(before, after) 0/(0,0), 0/(0,0)
misc=0 policy_id=1 auth_info=0 chk_client_info=0 vd=0
serial=00000294 tos=ff/ff ips_view=0 app_list=0 app=0
dd_type=0 dd_mode=0
```

If the priority on route ID 1 were changed from 5 to 20, what would happen to traffic matching that user's session?

- A. The session would remain in the session table, and its traffic would still egress from port1.
- B. The session would remain in the session table, but its traffic would now egress from both port1 and port2.
- C. The session would remain in the session table, and its traffic would start to egress from port2.
- D. The session would be deleted, so the client would need to start a new session.

Answer: A

Explanation:

<http://kb.fortinet.com/kb/documentLink.do?externalID=FD40943>

NEW QUESTION 122

Four FortiGate devices configured for OSPF connected to the same broadcast domain. The first unit is elected as the designated router The second unit is elected as the backup designated router Under normal operation, how many OSPF full adjacencies are formed to each of the other two units?

- A. 1
- B. 2

- C. 3
- D. 4

Answer: B

NEW QUESTION 123

View the exhibit, which contains the output of diagnose sys session list, and then answer the question below.

```
# diagnose sys session list
session info: proto=6 proto_state=01 duration=73 expire=3597 timeout=3600
flags=00000000 sockflag=00000000 sockport=0 av_idx=0 use=3
origin-shaper=
reply-shaper=
per_ip_shaper=
ha_id=0 policy_dir=0 tunnel=
state=may_dirty synced none app_ntf
statistic (bytes/packets/allow_err): org=822/11/1 reply=9037/15/1 tuples=2
origin->sink: org pre->post, reply pre->post dev=4->2/2->4 gw=10.200.1.254/10.0.1.10
hook=post dir=org act=snst 10.0.1.10:65464->54.192.15.182:80(10.200.1.1:65464
hook-pre dir=reply act=dnat 54.192.15.182:80->10.200.1.1:65464(10.0.1.10:65464)
pos/ (before, after) 0/(0/0), 0/(0,0)
misc=0 policy_id=1 auth_info=0 chk_client_info=0 vd=0
serial=00000098 tos=ff/ff ips_view=0 app_list=0 app=0
dd_type=0 dd_mode=0
```

If the HA ID for the primary unit is zero (0), which statement is correct regarding the output?

- A. This session is for HA heartbeat traffic.
- B. This session is synced with the slave unit.
- C. The inspection of this session has been offloaded to the slave unit.
- D. This session cannot be synced with the slave unit.

Answer: B

NEW QUESTION 125

A corporate network allows Internet Access to FSSO users only. The FSSO user student does not have Internet access after successfully logged into the Windows AD network. The output of the 'diagnose debug authd fssolist' command does not show student as an active FSSO user. Other FSSO users can access the Internet without problems. What should the administrator check? (Choose two.)

- A. The user student must not be listed in the CA's ignore user list.
- B. The user student must belong to one or more of the monitored user groups.
- C. The student workstation's IP subnet must be listed in the CA's trusted list.
- D. At least one of the student's user groups must be allowed by a FortiGate firewall policy.

Answer: AD

Explanation:

<https://kb.fortinet.com/kb/documentLink.do?externalID=FD38828>

NEW QUESTION 129

Which two configuration settings change the behavior for content-inspected traffic while FortiGate is in conserve mode? (Choose two.)

- A. IPS failopen
- B. mem failopen
- C. AV failopen
- D. UTM failopen

Answer: AC

NEW QUESTION 131

.....

Thank You for Trying Our Product

* 100% Pass or Money Back

All our products come with a 90-day Money Back Guarantee.

* One year free update

You can enjoy free update one year. 24x7 online support.

* Trusted by Millions

We currently serve more than 30,000,000 customers.

* Shop Securely

All transactions are protected by VeriSign!

100% Pass Your NSE7_EFW-7.0 Exam with Our Prep Materials Via below:

https://www.certleader.com/NSE7_EFW-7.0-dumps.html